

MPX-400MIC

ZONE SELECTOR MICROPHONE FOR MOD. SYSTEM MPX-4088



- ✓ Crystal clear voice pick-up
- ✓ Zone selection and warning broadcasting
- ✓ Musical alert tones
- ✓ Configuration software for PC

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:

<https://fonestar.com/MPX-400MIC>

DESCRIPTION

The MPX-4088 system is a highly versatile audio matrix, perfect for installations of any size, allowing a multitude of configuration options, DSP signal processing and integrated solutions to common problems such as feedback, covering almost any installation need.

MPX-400MIC is a microphone with zone selector for voice output and musical warning tones for audio matrix mod. MPX-4088.

Allows selection from 1 to 32 zones.

RJ-45, Cat 5e cable system connection.

For installations where there are various audio sources and audience areas such as shopping malls, hotels, conference rooms, stadiums, etc.

TECHNICAL CHARACTERISTICS

FEATURES	<p>Microphone with zone selector.</p> <p>Musical alert tones.</p> <p>Selection of zones and broadcasting of announcements in the audio matrix mod. MPX-4088.</p> <p>Power, signal, saturation and communication status indicator lights.</p> <p>LCD information screen.</p> <p>PC control software, customisation of zone names, microphone volume, volume and duration of musical tone and priority.</p>
MICROPHONE	<p>Electret condenser with flexo and ring light</p>
INPUTS	<p>1 balanced microphone, XLR 6.800 Ohm</p> <p>1 mini-USB port for uploading music alert tones in MP3 or WAV format</p> <p>1 RD port for connection to MPX-4088 matrix, RJ-45</p>
CONTROLS	<p>Microphone volume control and zone selector</p>
CONNEXION	<p>RJ-45 cable, Cat 5e</p>
PHANTOM	<p>12 V</p>



+ Info:

<https://fonestar.com/MPX-400MIC>

POWER SUPPLY	24 V DC, 100 mA, via RD port
DIMENSIONS	Microphone with flexo: 430 mm high Base: 176 x 53 x 166 mm depth
ACCESSORIES	Foam windshield



+ Info:

<https://fonestar.com/MPX-400MIC>