

PUBLIC ADDRESS / POWER AMPLIFIER / MULTI-CHANNEL

# FSD-2150E

DANTE MULTI-CHANNEL POWER STAGE



- ✓ Great power and sound quality in just 1 U rack
- ✓ 2 x audio channels
- ✓ High efficiency high reliability class D amplifier
- ✓ Secure, easy-to-connect euroblock connectors
- ✓ DANTE mod. compatible. FSD-22D

ESPECIALLY RECOMMENDED IN:



All sectors

## DESCRIPTION

Multi-channel PA power amplifier with 100 V line output.

Powerful power amplifier in only 1 U 19" rack.

Suitable for PA installations with 100 V or 70 V loudspeakers.

Class D amplifier with high efficiency and high reliability due to low-maintenance protection circuits.

Secure, easy-to-connect euroblock connectors.

DANTE support via optional FSD-22D model.

Great sound quality and low noise.

Reduced weight.

For multi-zone PA and piped music systems with 100 V or 70 V line loudspeakers. Commercial premises, sports centres, educational establishments, conference rooms, cafés, restaurants, theme parks, etc.



+ Info:

<https://fonestar.com/FSD-2150E>

## TECHNICAL CHARACTERISTICS

FEATURES	<p>2-channel PA power amplifier.</p> <p>100 V or 70 V output for PA installations.</p> <p>Highly efficient and reliable class D amplifier thanks to low-maintenance protection circuits.</p> <p>Safe and easily connectable euroblock connectors.</p> <p>Excellent sound quality and little noise.</p>
POWER	2 x 135 W RMS or 1 x 150 W RMS (single channel)
GAIN	40 dB
RESPONSE	100-15,000 Hz $\pm 3$ dB (-3 dB, with output level 10 dB below rated power)
DYNAMIC RANGE	>95 dBA (rated power)
DISTORSION	THD+N: <0.1% (1 kHz, 1/8 rated power, A-weighted)
CROSSTALK	>70 dB (rated power)
DAMPING FACTOR	>180 (1 kHz, 8 Ohm)
INPUTS	<p>2 balanced/unbalanced aux lines, euroblock, 20,000 Ohm/10,000 Ohm, 0.9-1.1 V RMS</p> <p>1 emergency/test, euroblock, 1 V RMS (0 dBV)</p>
OUTPUTS	1 GPIO fault indicator output, 5 V DC, euroblock
FUNCTIONS	<p>Forced ventilation with variable speed according to the temperature</p> <p>LED power, protection, priority and peak signal indicators</p> <p>Emergency input priority/contact closure test, euroblock</p> <p>Disabling/mute via contact closure, euroblock</p>
PROTECTION	Short circuit, open circuit, temperature, ultrasound and radio frequency



+ Info:  
<https://fonestar.com/FSD-2150E>

CONTROLS	Volume for each channel 100/70 V switch on rear panel
IMPEDANCE	100 and 70 V lines, euroblock
TEMPERATURE RANGE	Operation: 0°C ~ 50°C
POWER SUPPLY	230 V AC, 400 W maximum 115 V AC on demand
DIMENSIONS	483 x 44 x 380 mm depth. 1 U 19" rack
WEIGHT	4.75 kg
OPTIONAL	FSD-22D: DANTE expansion module
ACCESSORIES	Anti-slip adhesive pads



+ Info:  
<https://fonestar.com/FSD-2150E>