

PUBLIC ADDRESS / POWER AMPLIFIER / SINGLE CHANNEL

## FS-2601E

SINGLE CHANNEL POWER STAGE



- ✓ High power: 700 W maximum, 600 W RMS
- ✓ 4 and 8 Ω, 100 and 70 V speaker output
- ✓ Protection circuits: Temperature, short circuit and overload

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:  
<https://fonestar.com/FS-2601E>

## DESCRIPTION

Power amplifier, 700 W maximum, 600 W RMS with 4 and 8 Ohm loudspeaker output, 100 and 70 V lines.

## TECHNICAL CHARACTERISTICS

FEATURES	Mono power amplifier.
POWER	700 W maximum, 600 W RMS
RESPONSE	50-22,000 Hz $\pm$ 3 dB
DISTORTION	Harmonic: < 0.5%
INPUTS	1 balanced aux line, XLR and 6.3 mm jack 20,000 Ohm, 1 V RMS
OUTPUTS	1 balanced aux line, XLR and 6.3 mm jack
FUNCTIONS	Forced ventilation with variable speed according to the temperature Automatic compression of the input signal LED for temperature, protection, signal peak and output signal indicators
PROTECTION	3 circuits: temperature, short circuit and overload Switches on smoothly. RF filter 500 kHz - 80 MHz
CONTROLS	Tone: bass, mid and treble $\pm$ 12 dB General volume
IMPEDANCE	4 and 8 Ohm and 100 and 70 V lines, screw terminals and banana plugs
POWER SUPPLY	230 V AC, 1,000 W maximum Resettable 6 A fuse



+ Info:  
<https://fonestar.com/FS-2601E>

DIMENSIONS

483 x 89 x 435 mm depth. 2 U 19" rack

WEIGHT

17 kg



+ Info:  
<https://fonestar.com/FS-2601E>