

ZSM-1050

MULTI-ZONE MESSAGE SCHEDULER, BACKGROUND MUSIC PLAYER AND SIP CLIENT



ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Message programmer, events and background music player with 4 output zones.

Internal clock function with automatic daylight saving time update

Programmed, live message player and alarms. And plays background music from internal memory or USB/SD, creation of multiple background music channels.

Alarm activation through contact closure.

Easy programming with PC software, management via local area network (LAN) and internet.

TECHNICAL CHARACTERISTICS



+ Info:

<https://fonestar.com/ZSM-1050>

<p>FEATURES</p>	<p>Message scheduler, event scheduler, background music player and SIP client with 4 outgoing zones. Internal clock function with automatic daylight saving time update. Temporary scheduling of general purpose messages and outputs. Play live messages. Triggering of alarms and events by contact closure. Dedicated player for messages, alarms (internal memory) and VoIP. It does not interrupt background music. Ambient music player from USB/SD or internal memory with multi-channel creation. SIP protocol. PC software for programming, management and transfer of audio files via local area network (LAN) and internet. Priority of alarms and messages on background music inputs. 16 GB internal memory for audio files. USB port and SD card reader for audio file playback and software update.</p>
<p>INPUTS</p>	<p>1 background music aux, 2 x RCA 1 V 4 programmable inputs for alarm activation through contact closure, euroblock 1 ethernet, RJ-45</p>
<p>OUTPUTS</p>	<p>4 zones, 2 x RCA 2 V 4 general purpose relays, euroblock 2 link for future applications, RJ-45</p>
<p>POWER SUPPLY</p>	<p>100-240 V AC, 9 W and 24 V DC, 0.4 A</p>
<p>DIMENSIONS</p>	<p>435 x 45 x 220 mm depth. 1 U 19" rack</p>
<p>WEIGHT</p>	<p>2.7 kg</p>
<p>ACCESSORIES</p>	<p>Mounts for assembly in 19" rack</p>
<p>SOFTWARE</p>	<p>PC software ZSM-GO (included) Access via local area network (LAN) and internet Multiple ZSM control and management Message programming and general purpose outputs Alarm and alarm input configuration Creation and control of background music channels Audio file transfer and management Status monitoring</p>



+ Info:
<https://fonestar.com/ZSM-1050>