

# MIX-4LIVE

STUDIO MIXER.



## DESCRIPTION

4-channel stereo mixer with live streaming function, PC audio card and Bluetooth®/USB recorder/player.

Live streaming function, you can connect your smartphone or tablet and broadcast your performance live on your favourite platform, no need for anything else.

Connect the mixer to your PC as an audio card. You can play audio content from your PC and record audio on your PC simultaneously.

Bluetooth/USB recorder and player, play music or record the performance without PC.

Includes effects (delay and repeat) with level control, which will give an extra touch to your performances. It also has 48 V phantom power on channel 1 for the use of condenser microphones.

It has a very small and portable size, perfect for street artists, home music studios, small events or parties, etc. In addition, it only requires a 5 VDC, 2.1 A power supply, which can be provided by the adapter, by the USB port of a PC or laptop or through a power bank, which greatly increases the versatility and possibilities of use of this complete mixer.



Expand product information on:  
<https://fonestar.com/es/MIX-4LIVE>

**TECHNICAL CHARACTERISTICS**

FEATURES	<p>Stereo mixer with 2 mono channels and 1 stereo channel.</p> <p>Live streaming function, connect your smartphone to broadcast live.</p> <p>USB audio input/output for PC connection as an audio card, allows you to play audio from PC and record it simultaneously.</p> <p>Bluetooth receiver.</p> <p>USB recorder/player.</p> <p>2 digital effects (delay and repeat).</p>
USB PLAYER	<p>Plays or records MP3 files from USB</p> <p>USB-C port for connection to PC as audio card</p>
INPUTS	<p>2 balanced microphones/lines, combo (XLR, 600 Ohm 5 mV RMS and 6.3 mm jack, 47.000 Ohm 30 mV RMS)</p> <p>1 balanced/unbalanced stereo line channel, 2 x 6.3 mm jack/2 x RCA, 47,000 Ohm 300 mV RMS</p> <p>1 stereo auxiliary for live streaming, 3.5 mm TRRS jack, 47,000 Ohm 300 mV RMS</p> <p>1 mic, 3.5 mm mono jack, 600 Ohm 5 mV RMS</p> <p>1 USB/PC, stereo</p>
CONTROLS	<p>4 controls per channel: gain, 2-band EQ, volume and clip indicator light</p> <p>Effects level control</p> <p>Headphone volume</p> <p>Independent main output volume control</p>
FUNCTIONS	<p>2-band equaliser per channel</p> <p>Overload indicator and master output level indicator light</p> <p>Live streaming</p> <p>USB/PC</p>
OUTPUTS	<p>1 stereo main balanced/unbalanced, 2 x 6.3 mm jack/2 x RCA, 5 V RMS</p> <p>1 stereo auxiliary for live streaming, 3.5 mm TRRS jack, 500 mV RMS</p> <p>1 stereo headphone, 3.5 mm TRRS jack, 500 mV RMS</p> <p>1 USB/PC, stereo</p>
PHANTOM	<p>48 V on channel 1, selectable</p> <p>5 V at 3.5 mm jack plug on channel 1</p>
RESPONSE	<p>20-20,000 Hz</p>
DISTORTION	<p>Harmonic: 0.05 %</p>



Expand product information on:  
<https://fonestar.com/es/MIX-4LIVE>

S/N RATIO	> 68 dB
POWER SUPPLY	5 V DC, 2.1 A with adapter included
DIMENSIONS	175 x 55 x 190 mm depth
WEIGHT	0.6 kg
ACCESSORIES	3.5 mm TRRS male-male audio cable USB-A to USB-C power cable USB power adapter



Expand product information on:  
<https://fonestar.com/es/MIX-4LIVE>