

AUDIO AND CONSUMER ELECTRONICS / POWER ADAPTERS / DISPLAY / LAPTOP

# AD-2490

AC/DC 15 TO 24 V, 5 A, 90 W LAPTOP POWER ADAPTER



15-24 V DC, 2 A MAX. 90 W MAX.

- ✓ Powering and charging laptops, monitors and TVs
- ✓ Interchangeable connectors compatible with major brands
- ✓ Switched and stabilized
- ✓ High energy efficiency
- ✓ Protected against short circuit, overload, overcurrent and overvoltage

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:  
<https://fonestar.com/AD-2490>

## DESCRIPTION

AC/DC adapter with selectable voltage and 11 interchangeable connectors, compatible with most common laptops. Power supply and battery charger function. Switched circuit with low standby power consumption. High energy efficiency. Safe operation with short-circuit, overload, over-current and over-voltage protection. Power your notebook safely and efficiently. Power supply from 15 to 24 V DC, and maximum power consumption of 5 A or 90 W. Compatible with most notebooks; Acer, HP, Sony, Samsung, Dell, Asus, Fujitsu, LG, Benq and Toshiba, and monitors, TV etc.

## TECHNICAL CHARACTERISTICS

<p style="text-align: center;">FEATURES</p>	<p>AC/DC adapter battery charger for laptops, monitors and TVs with 15 to 24 V power supply and maximum power consumption of 5 A, 90 W max.</p> <p>7 different voltage settings.</p> <p>11 interchangeable connectors, compatible with notebooks, Acer, HP, Sony, Samsung, Dell, Asus, Fujitsu, LG, Benq and Toshiba, and common use in monitors and TV.</p> <p>Switched circuit with high energy efficiency.</p> <p>Low standby power consumption.</p> <p>LED power indicator.</p>
<p style="text-align: center;">POWER SUPPLY</p>	<p>POWER SUPPLY</p>
<p style="text-align: center;">OUTPUTS</p>	<p>Manual selection</p> <p>15 V, 5 A, 75 W</p> <p>16 V, 5 A, 80 W</p> <p>18 V, 5 A, 90 W</p> <p>19 V, 4.74 A, 90 W</p> <p>20 V, 4.5 A, 90 W</p> <p>22 V, 4.1 A, 90 W</p> <p>24 V, 3.75 A, 90 W</p>



+ Info:  
<https://fonestar.com/AD-2490>

CONNECTORS	<p>Connectors (mm):</p> <p>5.5 x 2.2</p> <p>A: 6.5 x 4.4 (Sony, Fujitsu with 16, 19 and 19.5 V inputs)</p> <p>B: 6.3 x 3 (Toshiba with 15 V input)</p> <p>C: 5.5 x 2.5 (Acer, HP/Compaq, Fujitsu, Toshiba with inputs 16, 18.5, 19, 19.5 V)</p> <p>E: 5.5 x 1.7 (Acer, Dell with 19 input)</p> <p>G: 4 x 1.7 (HP/Compaq with 19 input)</p> <p>H: 5.5 x 3 (Samsung with 16, 19 V inputs)</p> <p>I: 3-pin (Dell 20 V)</p> <p>P: 4.8 x 1.7 (Asus, HP/Compaq, LG, Sony, Benq with 18.5, 19 V inputs)</p> <p>Dell: 7.4 x 5 (Dell with 19.5 V input)</p> <p>HP: 7.4 x 5 (HP/Compaq with 18.5, 19 V inputs)</p>
STANDBY POWER CONSUMPTION	CONSUMO EN REPOSO
PROTECTION	Short-circuit, overload, overcurrent and overvoltage.
CABLE	<p>AC: 1.2 m</p> <p>DC: 1.2 m</p>
DIMENSIONS	6 x 3'5 x 14'5 cm fondo
WEIGHT	0.5 kg



+ Info:  
<https://fonestar.com/AD-2490>