

AUDIO AND CONSUMER ELECTRONICS / POWER ADAPTERS / COMMON APPLICATIONS

AD-2436

AC/DC 9 TO 24 V, 2 A, 36 W POWER ADAPTER







Power your devices safely and efficiently



Interchangeable connectors for the most common DC connections. Reversible polarity.



Switched and stabilized



High energy efficiency



Protected agains short-circuit, overload, overcurrent and overvoltage

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:

https://fonestar.com/AD-2436



DESCRIPTION

AC/DC adapter with selectable voltage and 7 interchangeable connectors, compatible with the most common DC connections. Switched-circuit power supply with low standby power consumption. High energy efficiency. Safe operation with short-circuit, overload, overcurrent and overvoltage protection. Power your devices safely and efficiently. For devices with 9 to 24 V DC power supply, and maximum power consumption of 2 A or 36 W. Compatible with many household electronic devices, such as speakers, LED strip lights, monitors, etc.

TECHNICAL CHARACTERISTICS

FEATURES	AC/DC adapter for devices with 9 to 24 V power supply and maximum power consumption of 2 A, 36 W max. 7 voltage settings. 7 interchangeable connectors, compatible with the most common DC connections. Reversible polarity. Switched circuit with high energy efficiency. Low standby consumption. LED power-on indicator.
POWER SUPPLY	POWER SUPPLY
OUTPUTS	Manual selection 9 V, 2 A, 18 W 12 V, 2 A, 24 W 13.5 V, 2 A, 27 W 15 V, 2 A, 30 W 18 V, 2 A, 36 W 20 V, 1.5 A, 30 W 24 V, 1.5 A, 36 W
CONNECTORS	Connectors (mm): 5.5 x 2.5 5 x 2.1 4.8 x 1.7 4 x 1.7 3.5 x 1.35 2.35 x 0.7 Jack 3.5
STANDBY POWER CONSUMPTION	CONSUMO EN REPOSO
PROTECTION	Short-circuit, overload, overcurrent and overvoltage.
CABLE	AC: 0.5m DC: 1.2 m
MEDIDAS	5 x 3.5 x 11 cm depth
WEIGHT	0.21 kg



+ Info:

https://fonestar.com/AD-2436