

MICROPHONES / WIRELESS MICROPHONES / ACCESSORIES

## FCM-660-TS

HEAD-WORN CONDENSER MICROPHONE



- ✓ High sensitivity, unidirectional
- ✓ 3.5 mm mono jack plug
- ✓ Elegant design
- ✓ Adjustable

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:  
<https://fonestar.com/FCM-660-TS>

## DESCRIPTION

Head-worn microphone. A lightweight and durable microphone. Reinforced structure with protected connections to withstand any situation. Special design to be placed on the head and position the capsule close to the mouth. Picks up sound predominantly in the direction of the speaker to avoid feedback. It offers great sound pickup. It can be used on wireless microphones or electret condenser microphone inputs, such as portable amplifiers.

## TECHNICAL CHARACTERISTICS

|               |  |
|---------------|--|
| FEATURES      | Unidirectional electret condenser capsule.<br>For wireless microphones or electret condenser microphone inputs.<br>Black colour.<br>Adjustable.  |
| RESPONSE      | 20-20,000 Hz   |
| SENSITIVITY   | -48 dB $\pm$ 2 dB (V/Pa)   |
| S/N RATIO     | >65 dB   |
| IMPEDANCE     | 680 Ohm  |
| POWER SUPPLY  | 1 to 10 V DC   |
| CABLE         | 1 m  |
| MATERIAL      | Steel  |
| CONNECTOR     | 3.5 mm mono male jack connector<br>Tip: signal. Body: ground (GND)   |
| COMPATIBILITY | FCM-660-TS, 3.5 mm mono jack for mods. MSHT-45P/MSH-135<br>FCM-660-TSM, 3.5 mm mono jack with male thread for mods. SONAIR<br>FCM-660-MC3, mini XLR 3-pin for mods. SONAIR-PRO, AKG and Gemini<br>FCM-660-MC4, mini XLR 4-pin for mod. MSH-236 |
| ACCESSORIES   | Wind-shield foam   |



+ Info:  
<https://fonestar.com/FCM-660-TS>