

PUBLIC ADDRESS / PUBLIC ADDRESS ACCESSORIES / IMPEDANCE METER

MI-21

IMPEDANCE METER FOR SPEAKER LINES



- ✓ 3 measurement scales
- ✓ Easy-to-read LCD display
- ✓ Easy handling.

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:
<https://fonestar.com/MI-21>

DESCRIPTION

Impedance meter for speakers or low impedance speaker lines, and 100 or 70 V line transformer.
An essential tool for PA installation. Allows the speaker line to be checked and measures the resulting impedance.

TECHNICAL CHARACTERISTICS

FEATURES	Impedance meter at 1 kHz for loudspeaker lines. Allows the impedance of loudspeaker lines to be checked and the estimated power necessary in a 100 or 70 V line installation, in order to choose the correct amplifier. 3 measurement ranges: 200 Ohm, 2 kOhm and 20 kOhm. Easy to read LCD screen. Power meter for 70 and 100 V line loudspeakers. Easy to use.
INPUTS	2 banana plugs to connect the measuring cables.
RESOLUTION (MEASUREMENT ACCURACY)	200 Ohm: 0.1 Ohm ($\pm 1\%$ ± 2) 2 kOhm: 1 Ohm ($\pm 1\%$ ± 2) 20 kOhm: 10 Ohm ($\pm 1\%$ ± 2)
POWER SUPPLY	9 V DC, 1 x 9V 6LR61 type battery
DIMENSIONS	87x 188 x 38 mm depth
WEIGHT	0.4 kg
ACCESSORIES	Rubber protector 2 sets of test leads: with alligator clip terminals and precision tips



+ Info:
<https://fonestar.com/MI-21>