

# MPX-430VS

VOLUME CONTROL AND ZONE SELECTION 2 OUTPUTS REMOTE CONTROL



- ✓ Allows for volume control and zone selection
- ✓ 2 x audio output channels
- ✓ LCD display

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:

<https://fonestar.com/MPX-430VS>

## DESCRIPTION

Volume control with two balanced audio outputs and zone allocation for audio matrix mod. MPX-4088.  
 Connection to the matrix via RJ-45, Cat 5e cable.

## TECHNICAL CHARACTERISTICS

FEATURES	<p>Volume control with two balanced audio outputs and zone allocation for audio matrix mod. MPX-4088.</p> <p>Connection to RD ports.</p> <p>Connection to the matrix via RJ-45, Cat 5e cable.</p> <p>LCD display with volume level information for the selected output.</p>
INPUTS	<p>1 RD port for connection to matrix MPX-4088, RJ-45</p>
OUTPUTS	<p>2 balanced line, euroblock, 240 Ohm, 7.74 V, assignable to digital channels 9/10 or 11/12.</p>
CONTROLS	<p>Volume control and zone allocation</p>
CONNECTION	<p>RJ-45, Cat 5e cable</p>
POWER SUPPLY	<p>24 V DC, 100 mA, RD port</p>
DIMENSIONS	<p>147 x 86 x 47 mm depth</p>
WEIGHT	<p>0.23 kg</p>
ACCESSORIES	<p>Surface box</p>



+ Info:  
<https://fonestar.com/MPX-430VS>