

PUBLIC ADDRESS / PUBLIC ADDRESS ACCESSORIES / TRANSFORMERS

# CV-1715

100 V LINE TRANSFORMERS FOR LOW IMPEDANCE LOUDSPEAKERS



- ✓ Z 100 V high input
- ✓ Z 4-8 Ω low output

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:  
<https://fonestar.com/CV-1715>

**DESCRIPTION**

100 V line transformer for low impedance loudspeakers.

**TECHNICAL CHARACTERISTICS**

POWER	100 V line: 15, 10, 5, 2.5, 1.25 W
IMPEDANCE	670, 1000, 2000, 4000, 8000 Ohm
OUTPUTS	Low Z for 4–8 Ohm speakers
DIMENSIONS	A: 71mm, B: 60mm, C: 50mm, D: 42mm, E: 41mm
WEIGHT	0.3 kg



+ Info:  
<https://fonestar.com/CV-1715>