

HIGH POWER / POWER AMPLIFIER / STEREO

SA-204

ETAPA DE POTENCIA ESTÉREO



- ✓ Great power and sound quality.
- ✓ High performance and stability
- ✓ It has protection circuits
- ✓ Very user-friendly and minimal set-up time

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Power amplifier

The SA series amplifiers deliver high power and sound quality with high performance and stability.

Operating and power modes:

Stereo and parallel: up to 150 + 150 W RMS@4 Ohm

Bridge: up to 200 W RMS@8 Ohm

High reliability with temperature, short circuit and overload protections.

Audio inputs with standard connectors: XLR and RCA with volume control for each channel.



+ Info:

<https://fonestar.com/SA-204>

Speaker outputs with screw terminals and banana plugs or speaker connector.

Very user-friendly and minimal set-up time.



Designed for professional use in different mobile events such as discos, concerts, festivals, meetings, etc., as well as for fixed installations in discotheques, pubs, auditoriums, etc.

TECHNICAL CHARACTERISTICS

FEATURES	Professional stereo power amplifier.
POWER	Stereo and parallel mode: 150 + 150 W RMS@4 Ohm 100 + 100 W RMS@8 Ohm Bridge mode: 200 W RMS@8 Ohm
PROTECTION	Temperature, short circuit and surge Forced ventilation
CONTROLS	Volume per channel Parallel/stereo/bridge operating mode selector GND lift earth disconnection
INPUTS	1 balanced aux line, XLR, 20,000 Ohm 1 V RMS 1 unbalanced aux line, RCA, 10,000 Ohm 1 V RMS
RESPONSE	10-50,000 Hz
DISTORTION	Harmonic: < 0.05 %
DAMPING FACTOR	> 150
S/N RATIO	> 85 dB
CROSSTALK	> 70 dB



+ Info:
<https://fonestar.com/SA-204>

SLEW RATE	30 V/ μ s
OUTPUTS	Loudspeakers: 4-8 Ohm stereo, screw terminals and banana plugs or loudspeaker connector 8 Ohm mono bridge, screw terminals and banana plugs or loudspeaker connector
POWER SUPPLY	230/115 V AC, 700 W maximum
DIMENSIONS	483 x 88 x 350 mm depth 2 U 19" rack
WEIGHT	7.8 kg



+ Info:
<https://fonestar.com/SA-204>