

MIX-3DJ

DJ MIXER



DESCRIPTION

Compact DJ mixer with 3 stereo channels and 1 microphone, with PC audio card and Bluetooth®/USB player.

Connect the mixer to your PC as an audio card, no drivers required. You can play audio content from your PC and record audio on your PC simultaneously.

Built-in Bluetooth receiver, plays music received from smartphones, tablets and other Bluetooth devices.

USB recorder and player, play music or record the event without the need for a PC.

It has a very small and portable size, perfect for small studios, events or parties, etc.

TECHNICAL CHARACTERISTICS



Expand product information on:
<https://fonestar.com/es/MIX-3DJ>

<p>FEATURES</p>	<p>Compact DJ mixer with 3 stereo channels and 1 microphone. USB audio input/output for PC connection as audio card, allows simultaneous PC audio playback and recording. Bluetooth receiver. USB recorder/player. CUE pre-listening. Output level indicator lights. Talk over for microphone level reduction (-15 dB).</p>
<p>USB PLAYER</p>	<p>Playback formats: WAV and MP3. MP3 recording. USB port for connection of USB sticks or connection to PC as audio card. Supports memory up to 128 GB</p>
<p>INPUTS</p>	<p>1 unbalanced mic, 6.3 mm jack, 1,000 Ohm 1 mV RMS 1 line/Bluetooth/USB/PC player, 2 x RCA, 10,000 Ohm 2 line/stereo phono, 2 x RCA, 10.000 Ohm 160 mV RMS/50.000 Ohm 4 mV RMS</p>
<p>OUTPUTS</p>	<p>1 stereo master, 2 x RCA, 600 Ohm 1.22 V RMS 1 stereo headphones, 6.3 mm jack 8 Ohm 200 mW</p>
<p>FUNCTIONS</p>	<p>CUE pre-listen Output level indicator Talk over for level reduction with mic (-15 dB)</p>
<p>RESPONSE</p>	<p>20-20,000 Hz</p>
<p>DISTORTION</p>	<p>Harmonic: <0.04%</p>
<p>S/N RATIO</p>	<p>> 80 dB</p>
<p>POWER SUPPLY</p>	<p>12 V DC, 1 A with adapter included</p>
<p>DIMENSIONS</p>	<p>235 x 55 x 135 mm depth</p>
<p>WEIGHT</p>	<p>0.7 kg</p>



Expand product information on:
<https://fonestar.com/es/MIX-3DJ>