

MIX-8PRO

STUDIO MIXER.



DESCRIPTION

Professional 8-channel stereo mixer with PC audio card, USB recorder/player and Bluetooth® receiver.

Connect the mixer to your PC as an audio card. You can play the audio content of your PC via USB connection. USB recorder and player, play music or record the event without PC.

Includes 24-bit digital effects processor (16 effects), which will give an extra touch of quality to your events. Also features 48 V phantom power for use with condenser microphones.

Ideal for use at all kinds of events, press rooms, live performances, concerts, etc.

TECHNICAL CHARACTERISTICS

FEATURES

Professional 8-channel mixer with 2 outputs and independent volume controls.
 USB audio input for connection to PC as audio card, allows to play audio from PC.
 Bluetooth receiver.
 USB recorder/player.
 16 digital effects processor.



Expand product information on:
<https://fonestar.com/es/MIX-8PRO>

Poigono Trascueto. 39600 Revilla de Camargo. Cantabria (España)

USB PLAYER	<p>Playback formats: WAV and MP3</p> <p>MP3 recording</p> <p>USB port for connection of USB drives or connection to PC as audio card</p> <p>Supports memory up to 128 GB</p>
INPUTS	<p>8 balanced XLR mics, 600 Ohm 2 mV (LED peak, 1 kHz, 20 mV RMS)</p> <p>8 unbalanced lines, 6.3 mm jack, 47.000 Ohm 45 mV (LED peak, 1 kHz, 180 mV RMS)</p> <p>2 balanced returns, 2 x 6.3 mm jack, 47.000 Ohm 300 mV RMS</p>
OUTPUTS	<p>1 stereo main (2 x XLR or 2 x 6.3 mm jack), 5 V RMS</p> <p>1 stereo line, 2 x RCA, 5 V RMS</p> <p>1 post-fader send, 6.3 mm jack, 5 V RMS</p> <p>1 stereo headphone, 6.3 mm jack</p>
CONTROLS	<p>Mic/line: low-cut filter (18 dB/octave, 75 Hz), gain, bass (± 15 dB, 80 Hz), mid (± 15 dB, 2,500 Hz), treble (± 15 dB, 12,000 Hz), aux/EFX send, pan, mute and slide volume control</p> <p>USB recorder/player: mode, play/pause/rec, song forward/reverse, bass (± 15 dB, 80 Hz), treble (± 15 dB, 12,000 Hz) and slider volume control</p> <p>Main: sliding volume control</p> <p>Phones: volume control</p> <p>Post-fader aux send: volume control</p> <p>Aux returns: volume control</p> <p>DSP effects processor: effect selection, repeat and slider volume control</p>
FUNCTIONS	<p>Sliders per channel</p> <p>3-band EQ on channels 1 to 8</p> <p>2-band equaliser on USB recorder/player</p> <p>Overload and master output level indicator lights</p>
PHANTOM	48 V, selectable
RESPONSE	20-20,000 Hz
DISTORTION	Harmonic: 0.07 %
S/N RATIO	> 65 dB
POWER SUPPLY	100-240 V AC, 20 W maximum
DIMENSIONS	390 x 85 x 320 mm depth



Expand product information on:
<https://fonestar.com/es/MIX-8PRO>

WEIGHT

3.8 kg

OPTIONAL

SM-8PRO: mounts for assembly in 19" rack



Expand product information on:
<https://fonestar.com/es/MIX-8PRO>