

AUDIO AND CONSUMER ELECTRONICS / POWER ADAPTERS / COMMON APPLICATIONS

# AD-1218

AC/DC 3 TO 12 V, 1.5 A, 18W POWER ADAPTER



3-12 V DC, 1,500 mA    18 W MAX.

- ✓ Power your devices safely and efficiently
- ✓ Interchangeable connectors for the most common DC connections. Reversible polarity.
- ✓ Switched and stabilized
- ✓ High energy efficiency
- ✓ Short circuit, overload, overcurrent and overvoltage protections

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:  
<https://fonestar.com/AD-1218>

## DESCRIPTION

AC/DC adapter with selectable voltage and 8 interchangeable connectors, compatible with the most common DC connections. Switched-circuit power supply with low standby power consumption. High energy efficiency. Safe operation with short-circuit, overload, overcurrent and overvoltage protection. Power your devices safely and efficiently. For devices with 3 to 12 V DC power supply and maximum power consumption of 1.5 A, 18 W. Compatible with many household electronic devices, such as routers, speakers, LED strip lights, cameras, etc.

## TECHNICAL CHARACTERISTICS

|                           |  |
|---------------------------|--|
| FEATURES                  | <p>AC/DC adapter for devices with 3 to 12 V power supply and maximum power consumption of 1.5 A, 18 W max.</p> <p>7 voltage settings.</p> <p>8 interchangeable connectors, compatible with the most common DC connections.</p> <p>Reversible polarity.</p> <p>Switched circuit with high energy efficiency.</p> <p>Low standby consumption.</p> <p>LED power-on indicator.</p> |
| POWER SUPPLY              | POWER SUPPLY   |
| OUTPUTS                   | <p>Manual selection</p> <p>3 V, 1.5 A, 4.5 W</p> <p>4.5 V, 1.5 A, 6.75 W</p> <p>5 V, 1.5 A, 7.5 W</p> <p>6 V, 1.5 A, 9 W</p> <p>7.5 V, 1.5 A, 11.25 W</p> <p>9 V, 1.5 A, 13.5 W</p> <p>12 V, 1.5 A, 18 W</p>   |
| CONNECTORS                | <p>Connectors (mm):</p> <p>5.5 x 2.5</p> <p>5 x 2.1</p> <p>4 x 1.7</p> <p>3.5 x 1.35</p> <p>2.35 x 0.7</p> <p>3.5 Jack</p> <p>USB A</p> <p>Micro USB B</p>   |
| PROTECTION                | Short-circuit, overload, overcurrent and overvoltage.  |
| STANDBY POWER CONSUMPTION | 100-240 V CA, 0.1 W máx.   |
| CABLE                     | 1.2 m CC   |
| DIMENSIONS                | 4.5 x 7 (3.5 without AC plug) x 9 cm depth   |
| WEIGHT                    | 0.12 kg  |



+ Info:  
<https://fonestar.com/AD-1218>