

MICROPHONES / WIRELESS MICROPHONES / ACCESSORIES

FCM-660-MC3

HEAD-WORN CONDENSER MICROPHONE



PHANTOM
1-10 V DC

- ✓ High sensitivity, unidirectional
- ✓ Mini XLR 3 pin connector
- ✓ Reinforced design
- ✓ Adjustable

ESPECIALLY RECOMMENDED IN:



All sectors



+ Info:
<https://fonestar.com/FCM-660-MC3>

DESCRIPTION

Head-worn microphone. A lightweight and durable microphone. Reinforced structure with protected connections to withstand any situation. Special design to be placed on the head and position the capsule close to the mouth. Picks up sound predominantly in the direction of the speaker to avoid feedback. It offers great sound pickup. It can be used on wireless microphones or electret condenser microphone inputs, such as portable amplifiers.

TECHNICAL CHARACTERISTICS

FEATURES	Unidirectional electret condenser capsule. For wireless microphones or electret condenser microphone inputs. Black colour. Adjustable.
RESPONSE	20-20,000 Hz
SENSITIVITY	-48 dB \pm 2 dB (V/Pa)
S/N RATIO	>65 dB
IMPEDANCE	680 Ohm
POWER SUPPLY	1 to 10 V DC
CABLE	1 m
MATERIAL	Steel
CONNECTOR	3-pin female Mini XLR connector Pin 1: ground (GND). Pin 3: signal
COMPATIBILITY	FCM-660-TS, 3.5 mm mono jack for mods. MSHT-45P/MSH-135 FCM-660-TSM, 3.5 mm mono jack with male thread for mods. SONAIR FCM-660-MC3, mini XLR 3-pin for mods. SONAIR-PRO, AKG and Gemini FCM-660-MC4, mini XLR 4-pin for mod. MSH-236
ACCESSORIES	Wind-shield foam



+ Info:
<https://fonestar.com/FCM-660-MC3>